


SVM7940C Series

Multi-Melody IC



- 512 Words Melody ROM
- Piezo Transducer Direct Drive
- 4 Melodies Max. (Binary Code Selection)
8 Melodies (Serial Trigger Selection)

DESCRIPTION


The SVM7940C Series are CMOS IC circuits which contain a programmed ROM for playing tunes. It is designed for electronic watches or music boxes. The SVM7940C series has 512 notes and a maximum of 4 or 8 melodies may be selected by switch.

NOTE: These are ongoing user service products.

FEATURES

- Mask programmable up to 512 notes
- Maximum 4 or 8 melodies can be selected by switch
- Can be driven by DC pulse or AC pulse (Mask selection)
- Piezo transducer direct drive
- NPN transistor coil drive
- Melody can be stopped halfway by switching (Only applied to one-shot mode)
- Sound demonstration capability
- Mono tone
- Available for high impedance buzzers
- Hourly chime (Option)
- PackageDIP-16pin (plastic)

BLOCK DIAGRAM



PIN CONFIGURATION

DIP-16pin			
TST	1	16	V _{DD}
NC	2	15	(CHK ₀)
OSC1	3	14	(CHK ₁)
OSC2	4	13	STP
MS2	5	12	BD
MS1	6	11	BD
MT	7	10	(CHK ₂)
V _{SS}	8	9	TD

■ ABSOLUTE MAXIMUM RATINGS

(V_{SS} = 0V)

Rating	Symbol	Value	Unit
Supply voltage	V _{DD}	−0.3 to 5.0	V
Input/Output voltage	V _{I/O}	−0.2 to V _{DD} +0.2	V
Operating temperature	T _{opr}	−20 to +65	°C
Storage temperature	T _{stg}	−65 to +150	°C
Soldering temperature and time	T _{sol}	260°C, 10s (at lead)	—

■ ELECTRICAL CHARACTERISTICS

(V_{SS} = 0V, Ta = 25°C)

Characteristic	Symbol	Condition	Min.	Typ.	Max.	Unit
Operating voltage	V _{DD}		1.2	1.5	2.0	V
"1" input voltage	V _{IH}		V _{DD} −0.1	—	V _{DD}	V
"0" input voltage	V _{IL}		V _{SS}	—	V _{SS} +0.1	V
"1" input current (Terminal OSC1)	I _{IH1}	V _{DD} =1.5V, V _{IH1} =V _{DD}	—	—	0.05	μA
"1" input current (Terminal SEL1, SEL2)	I _{IH2}	V _{DD} =1.5V V _{IH2} =V _{DD}	Serial tigger selection	1.5	—	15
		Binary code selection	Standby	—	—	0.05
			Play	1.5	—	15
"1" input current (Terminal STP)	I _{IH3}	V _{DD} =1.5V V _{IH3} =V _{DD}	Standby	—	—	0.05
			Play	1.5	—	15
"1" input current (Terminal MT, TST)	I _{IH4}	V _{DD} =1.5V, V _{IH4} =V _{DD}	1.5	—	15	μA
"1" input current (Terminal TST, OSC1, SEL1, SEL2, MT, STP)	I _{IL}	V _{DD} =1.5V V _{IL} =V _{SS}	—	—	0.05	μA
"1" output current (Terminal OSC2)	I _{OH1}	V _{DD} =1.2V, V _{OH1} =1.1V	3.0	—	30	μA
"0" output current (Terminal OSC2)	I _{OL1}	V _{DD} =1.2V, V _{OL1} =0.1V	3.0	—	30	μA
Input amplitude	A _I	V _{DD} =1.5V, when external reference signal applied to OSC1	$\left \frac{V_{DD}}{2}\right \pm 0.3$	—	—	V
Average current drain during standby	I _{STB}	V _{DD} =1.5V, All terminals open	—	—	0.3	μA
Average current drain during play	I _{OPR}	V _{DD} =1.5V, f _{OSC} =32.768kHz V _{DD} connected to terminal MT	—	40	80	μA

■ OSCILLATION CHARACTERISTICS (CR Oscillation)

(V_{SS} = 0V, Ta = 25°C)


Characteristic	Symbol	Condition	Min.	Typ.	Max.	Unit
Oscillator frequency	f _{OSC}	V _{DD} = 1.5V VR=620kΩ	−30	32.768kHz	+30	%
Oscillator self-start voltage	V _{STA}	VR=620kΩ	1.2	—	—	V
Oscillator stop voltage	V _{STP}	VR=620kΩ	—	—	1.2	V

■ SVM7940 SERIES (Mask selection)

Type	Oscillation	Tune mode	Tune selection
SVM7942	CR self OSC.	Level hold	Serial trigger selection
SVM7943	CR self OSC.	One-shot	Serial trigger selection

■ BASIC EXTERNAL CONNECTION

● SVM7942, SVM7943



■ **CIRCUIT FOR SELECTION:** at a position **A** of above block diagram 1 & 2.




■ **SELECTION OF SONG AND SOUND DEMONSTRATION** (Mask selection)

Options \ Terminal	SEL2	SEL1	MT
(1)	Select song only	Sound demo only	Alarm input or sound demo input
(2)	Select song only	Select song and sound demo	
(3)	Only when both SEL1 and SEL2 are triggered, select song and sound demo, or select song only.		
(4)	Select song by binary code of SEL1 and SEL2 (Max.4 tunes)		

■ **PACKAGE DIMENSIONS**

Plastic DIP-16pin



Unit: mm
(inch)

NOTICE

No part of this material may be reproduced or duplicated in any form or by any means without the written permission of Seiko Epson. Seiko Epson reserves the right to make changes to this material without notice. Seiko Epson does not assume any liability of any kind arising out of any inaccuracies contained in this material or due to its application or use in any product or circuit and, further, there is no representation that this material is applicable to products requiring high level reliability, such as, medical products. Moreover, no license to any intellectual property rights is granted by implication or otherwise, and there is no representation or warranty that anything made in accordance with this material will be free from any patent or copyright infringement of a third party. This material or portions thereof may contain technology or the subject relating to strategic products under the control of the Foreign Exchange and Foreign Trade Control Law of Japan and may require an export license from the Ministry of International Trade and Industry or other approval from another government agency.

All product names mentioned herein are trademarks and/or registered trademarks of their respective companies.

©Seiko Epson Corporation 1998 All rights reserved.

SEIKO EPSON CORPORATION**ELECTRONIC DEVICES MARKETING DIVISION****Electronic Device Marketing Department
IC Marketing & Engineering Group**

421-8, Hino, Hino-shi, Tokyo 191-8501, JAPAN
Phone: +81-(0)42-587-5816 Fax: +81-(0)42-587-5624

ED International Marketing Department I (Europe & U.S.A.)

421-8, Hino, Hino-shi, Tokyo 191-8501, JAPAN
Phone: +81-(0)42-587-5812 Fax: +81-(0)42-587-5564

ED International Marketing Department II (Asia)

421-8, Hino, Hino-shi, Tokyo 191-8501, JAPAN
Phone: +81-(0)42-587-5814 Fax: +81-(0)42-587-5110

Electric Device Information of EPSON WWW server

<http://www.epson.co.jp>

